# METHOD AND APPARATUS FOR IMPROVED PERFORMANCE OF FLASH MEMORY CELL DEVICES

Yuesong He

Kent Kuohua Chang

R. Lee Tan

FIELD OF THE INVENTION

The present invention relates to flash memory or EEPROM memory cells using isolated gate floating gates.

BACKGROUND OF THE INVENTION

Flash memory cell arrays using isolated gate floating gate MOSFET transistors store charge on the floating gates which modify the threshold voltage ("V_t") of the MOSFETs of the memory cells. These memory cells can be arranged in a NAND gate or NOR gate architecture for purposes of reading and writing the respective cells in the array.

To achieve higher density, the feature size of these cells is currently at a low sub-micron level. As the channels of these transistors become shorter, a number of detrimental short channel effects are seen. One solution to avoid these effects, such as "punch-through", is to reduce the dopant levels of the source and drain of the MOS devices. Reducing source and drain dopant levels, however, cause an increase in the series resistance of a memory cell device, thus reducing the read current to an unacceptably low level.

There is thus a need for a method and an apparatus that maintain a sufficiently high read current in a floating gate MOSFET transistor, even with a reduced source and drain dopant levels. In the past, retrograde doping distribution are created by ion

implantation and subsequent annealing to modify the underlying p-type or n-type well dopant concentration. Such a process is described in Yang, Microelectronic Devices, McGraw-Hill, 1988, and United States Patent

5   No. 5,045,898, issued to Chen et al. on August 30, 1991, entitled CMOS INTEGRATED CIRCUIT HAVING IMPROVED ISOLATION, and United States Patent No. 5,091,332, issued to Bohr et al. on February 25, 1992, entitled SEMICONDUCTOR FIELD OXIDATION PROCESS, the disclosures

10   of which are hereby incorporated by reference. Retrograde dopant distribution in the channel region has also been used to create buried n-channel devices (PMOS) to deal with short channel effects, as is shown in United States Patent No. 5,122,474, issued to

15   Harrington III on June 16, 1992, entitled METHOD OF FABRICATING A CMOS IC WITH REDUCED SUSCEPTIBILITY TO PMOS PUNCHTHROUGH, the disclosure of which is hereby incorporated by reference.

Other methods addressing punch-through and other

20   short-channel effects have included buried back gates, as shown in United States Patent No. 5,877,049, issued to Liu et al. on March 2, 1999, entitled METHOD FOR FORMING ADVANCED TRANSISTOR STRUCTURES WITH OPTIMUM SHORT CHANNEL CONTROLS FOR HIGH DENSITY HIGH

25   PERFORMANCE INTEGRATED CIRCUITS, the disclosure of which is hereby incorporated by reference.

SUMMARY OF THE INVENTION

The present invention relates to providing dopant

30   in the channel area of a well structure for NAND type memory cells formed by isolated gate floating gate transistors. The dopant is provided by ion implantation with a tilt angle around the existing floating gate structure at a selected stage of the

-2-

fabrication process following the formation of the control/floating gate structure. The process of the present invention may occur before or after the implantation of the source and drain dopants. The tilt
5 angle implantation forms a retrograde distribution from the channel surface, which is also concentrated laterally toward the centerline axis of the gate structure and decreases towards the opposing source and drain regions. This retrograde distribution promotes
10 buried-channel-like performance of the transistors connected in series in the NAND gate memory architecture and reduces series resistance of the series-connected floating gate MOS devices. Consequently, a reduction in source/drain dopant levels
15 is achieved. Decreasing the series resistance in the bit line provides higher the output current that is available for sensing for a given selected V_{cc}.

BRIEF DESCRIPTION OF THE DRAWING

20   Fig. 1 shows a schematic diagram of a portion of a basic flash memory cell arrangement in a NAND gate architecture; and,

        Fig. 2 shows a cross-sectional view of the isolated gate floating gate NMOS transistors forming
25 the NAND gate architecture shown in Fig. 1, at an intermediate stage of manufacture.

        The use of similar reference numerals in different Figures indicates similar or identical items.

DETAILED DESCRIPTION OF A PREFERRED EMBODIMENT
30
        Fig. 1 shows a schematic view of a portion of a basic flash memory cell arrangement 10 in a NAND gate architecture. Arrangement 10 includes isolated gate floating gate MOSFET transistors 14, 16, 20 and 22

-3-

connected together in series by common source/drain leads along a bit line of a memory cell array (not shown).

In the NAND gate architecture, a number of memory transistors ("cells"), usually a multiple of 8, are connected along a "bit line" of a memory array. Each of transistors 14, 16, 20 and 22 is associated respectively with a word line. For example, the gate of transistor 14 is connected to WL0, the gate of transistor 16 is connected to WL1, the gate of transistor 20 is connected to WLn-1, and the gate of transistor 22 is connected to WLn.

As shown in Fig. 1, the drain of transistor 14 is connected to the source of an insulated gate NMOS selection transistor 12. The drain of transistor 12 is connected to a voltage source V_{cc} and the gate of transistor 12 is connected to receive a signal SD. At the opposite end of arrangement 10 is provided another insulated gate NMOS selection transistor 24. The drain of transistor 24 is connected to the source of transistor 22 and the source of transistor 24 is connected to ground. The gate of transistor 24 is connected to the source of a signal SS. Together transistors 12 and 24 select for reading the stored content of one of memory transistors 14, 16, 20, 22 when an associated one of the word lines WL0-WLn is selected.

Fig. 2 shows a cross sectional view of a plurality of memory cells of arrangement 10 at an intermediate stage of manufacture. NMOS transistors 12, 14, 16 and 18 are depicted as being formed in a p-type well 32 of n-type mono-crystalline semiconductor substrate 30. Source/drain regions 60, 62, 64 and 66, interconnect the devices 12, 14, 16 and 18 in series along the bit

line. The source/drain regions 40, 60, 62, 64 and 66
are doped with a relatively light concentration of n-
type dopant, indicated by "n⁻".

sub 94

In one embodiment, select transistor 12 has an
amorphous poly-silicon ("poly") gate 44s (formed as
further explained below) and separated from a channel
region 70 between drain region 40 and source region 60
by an oxide layer 50 which may be, for example, 168 Å
thick. Select transistor 12's poly gate 44s is covered
by a thin tungsten silicide layer 58.

sub 95

Oxide layer 50 may be thermally grown using a dry
oxidation process at about 1050° C. to a thickness of
about 148 Å. A photoresist mask is then used to
pattern for an etching step that exposes the substrate
outside of the select transistors (e.g., select
transistor 12). Then, a film of about 87 Å of oxide is
formed as tunnel oxide 52 using a dry thermal oxidation
process at about 1050° C. Due to the slower growth
rate on oxide layer 50, oxide layer 50 only increases
about 20 Å to a thickness of about 168 Å.

A polysilicon layer 56 is then deposited as a
doped amorphous polysilicon layer using an in situ
chemical vapor deposition ("CVD") technique which
reacts silane (SiH_4) at around 530°C and 400 mT.
Polysilicon layer 56, which subsequently provides
floating gates 56m1, 56m2, 56m3, is insulated from the
channel regions 72, 74, 76, respectively, by tunnel
oxide layer 52. An oxide-nitride-oxide ("ONO") tri-
layer 54, for subsequently providing insulators 54m1,
54m2, 54m3 of transistors 14, 16 and 18, is formed by a
first HTO oxide deposition of about 50 Å of oxide at
750°C, followed by deposition at about 760°C of a
nitride ($Si_3 N_4$) layer of 80 Å, and a wet thermal
nitride oxidation at about 950°C by wet O_2, thus forming

-5-

an oxide layer of about 45 Å thick.

Phosphorous doped polysilicon of about 1200 Å thick is then deposited, using silane at about 530°C and at about 400 mT of pressure, for subsequently

5 forming control gates 44s, 44m1, 44m2, 44m3 of transistors 12, 14, 16, and 18. A 1400 Å tungsten silicide (Wsix) layer 58, for subsequently forming tungsten silicide layers 58s, 58m1, 58m2, 58m3 of transistors 12, 14 and 18, is then deposited by CVD

10 using a mixture of WF_6 gas and silane gas. Patterning using photoresist and subsequent etching steps provide control gates 44s, 44m1, 44m2, 44m3, ONO structures 52m1, 52m2 and 52m3, and floating gates 56m1, 56m2 and 56m3 for the transistors shown.

15 A retrograde distribution of dopant is then introduced by ion implantation into the channel regions 72, 74 and 76, while channel region 70 under select transistor 12 is masked by photoresist. The retrograde distribution of dopant is accomplished by implanting an

20 n-type dopant (e.g., arsenic) at a tilt implant angle of, for example, 45° to vertical. Other tilt angles may also be suitable. The implantation can be made with a "batch-type" machine or with a single-wafer machine. In a batch-type machine, the wafer is rotated

25 during the tilt implantation process. In a single-wafer machine, the implantation is done with a zero degree twist and a 180 degree twist (i.e., an tilt implantation through one side of source/drain regions 60, 62, and 64, followed by a like tilt angle

30 implantation deposition through the source/drain regions 62, 64 and 66). Implantation energies between 80 and 110 KeV are suitable, forming resulting dopant concentrations of about 2×10^{-12} to 8×10^{-13} atoms per cm^2.

In a batch-type machine, the resulting dopant
concentration is generally a frusto-conical
distribution at region 80 axially displaced about a
target area in the p-type well 32 beneath channel
5   regions 72, 74, 76. In a single-wafer machine, region
80 extends in the channel region parallel to the bit
line on each side of the centerline of each channel.
After an annealing step, region 80 has a dopant
distribution that increases from the level in the
10   substrate closest to the tunnel oxide 52 to the level
of the target area and then decreases down through the
substrate. In addition, region 80 has a lateral
distribution which tends to be highest toward the
centerline axis around the target area, and decreases
15   in the direction toward opposing source/drain regions
(e.g., source/drain regions 60 and 62 for transistor
14, source/drain regions 62 and 64 for transistor 16).

The retrograde dopant distribution in the channel
provides additional carriers (e.g., electrons in the
20   case of an NMOS device) in the channel and decreases
the series channel resistance, so that transistors 14,
16 and 18 operate in a manner similar to NMOS buried
channel devices.

The present invention has been described in
25   general terms to allow those skilled in the art to
understand and utilize the invention, and in relation
to a specific embodiment. The present invention is not
limited to the preferred embodiment, and may be
modified in a number of ways within the scope of the
30   present invention. For example the specific materials
and layers of the gate structures of the isolated gate
floating gate MOS transistors may be modified. Other
dopants may be added to modify the profiles and
concentrations of the source/drain regions and the p-

well in addition to those described herein.